



M1000 Remote Control Pairing Guide

1. Connect the camera to the power supply and wait for the camera initialization to complete, till the camera can output video normally.

2. Clear the paired status of the remote control:

Press the remote control pairing button (Figure 2) + OK button at the same time, and keep pressing until the remote control indicator shows a steady red light. Release the button to successfully clear the remote control paired status.

3. Trigger the camera to enter the remote control pairing mode:

Use the card pin to poke the recovery hole of the camera, that is, press the camera recovery button (Figure 1). When entering the pairing mode normally, the camera LED light will switch to the remote control matching mode, and the LED light will switch to blue, with a marquee effect. (Note: Each time you enter the pairing mode, there is only 15s operation time. After the timeout, it will automatically exit the pairing mode. At this time, the LED is not a blue marquee effect. If you need to pair again, you need to press the restore button again to enter the remote control pairing mode again.)

4. Start pairing:

Press and hold the pairing button on the remote control (as shown in Figure 2), keep pressing, and wait for the matching to complete. When the pairing is

successful, the camera's LED light will be blue with a flashing effect. After the pairing is successful, the camera can be operated by the remote control. If the pairing fails, please repeat steps 2, 3, 4 until the matching is successful.



(Figure 1: Reset hole)



(Figure 2: Pairing button)